

22.86cm (9)

Color TFT LCD Display



Features

- 22.86cm (9) TFT-LCD digital touch screen, can monitor entrance, outdoor situation anytime and work with a door camera for a second calling
- Remote unlocking
- Directly call can talk with center unit, and send alarm information.
- Call any other indoor unit in LAN system
- Download chord ring tones from management center PC and setup mute status
- Call elevator
- Call divert to guard center
- Household appliance control
- Support voice, pictures, message checking function
- Accept service from center unit
- Max 4 indoor units work together
- Support remote upgrading function

Specification

Model	S-9LCD
LCD	22.86cm (9) TFT-LCD
Input voltage	DC18V
Sensitivity	20mV
Distortion	5%
Display Pixel	384000 dots
Working Current	350mA ± 20%
Quiescent current	200 mA ± 20%
Output power	50mW
Video transmission	75 cable
Display time	about 60 S
Network port	RJ45
Network transmission mode	TCP/IP
Transmission range	Router or PBX less than 100m, FOT more than 100m
Working Humidity	45% ~ 95%
Storage temperature	- 15°C ~ 55°C

IP Villa Intercom Indoor Station

